

## Installation

---

### Getting Started

#### What's Included:

- VoIP of North America (ATA) Broadband Phone Adapter
- Ethernet Cable
- AC Power Adapter

#### Equipment you will need:

- Broadband Connection (DSL, Cable or other high-speed Internet connection)
- Touchtone Phone
- Router (If you want to share your Internet connection with other equipment or computers.)

**Note:** If you ordered VoIP -NA ATA you will receive a Linksys (Sipura) 2100 adapter that has a built in one port router.

#### Installation:

- Remove the phone adapter (ATA) from the shipping box.
- Turn off the power to all devices including your Cable/DSL modem and Router.
- Insert one end of Ethernet cable into the LAN port of the adapter.

**Note:** Insert the Ethernet cable into the WAN port of adapter and connect your computer to its LAN port (If needed.).

- Connect the other end of the cable to your DSL/Cable Modem.

**Note:** If you have a Router and DHCP enabled on it, you should connect the Ethernet Cable to its LAN port.

- Insert the telephone cable into phone port (1) of the ATA device.
- Connect the telephone cable to your touchtone telephone.
- Turn the power on the Cable/DSL modem (wait 1 minute).
- Connect the AC power adapter (power-up) to the ATA device.
- Wait; The green STATUS Light on the back of your ATA device will blink for up to 1 minute. Once the light stops blinking and remains on, you are ready to start making calls.

**Note:** If you are having problems and are unable to hear dial tone or make calls please contact our 24/7 technical support center at 1-888-277-8647.